CONVY-DCDC-800V-15-RA-00 (SINGLE CONVERTER)

Maximum output power according to Vlow side and Vhigh side

Map power capability according to low side and high side voltage

- Tame-Power DC/DC converters embed a powerful software that permanently calculates the maximum power the device can transfer.
- The calculation is done in real-time, according to the values of low side voltage and high side voltage.
- The Power Maps aim to bring you a clear overview of how the features change according to the operating point.
- This allows you to optimize the overall performance of your whole system by selecting the best voltage ranges to operate.

Max output power (kW) when the DCDC converter operates at Vlow side = 110V, Vhigh side = 180V

Vlow side \ Vhigh side	100	120	140	160	180	200	220
85	2	4	6	7	7	8	9
90	2	4	6	8	8	8	10
95	1	3	6	8	8	9	11
100		2	5	8	8	10	12
110			4	8	10	12	12
120				8	10	12	14
130				8	10	12	14
140				6	8	12	14
150				6	8	12	16
160					4	10	14

Boost mode (in kW)

Vlow \ Vhigh	40	50	60	70	80	90	100	115	130	145	160	175	190	205	220	235	250	265	280	295	310	325	340	355	370	385	400	415	430	445	460	475	490	505	520	535	550	565	580	595	610	625	640	655	670	685	700	715	730	745	760	775	790	800
35																																																							
40											1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
45					1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
50				1	1	1	1	1	1	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	1	0	0	0	0	0	0	0
60				1	1	2	2	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	2	2	0	0	0	0	0	0
70					1	3	3	3	4	4	4	4	4	4	4	4	4	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	5	4	1	0	0	0	0	0
80					1	2	4	4	4	5	5	5	5	5	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	4	2	0	0	0	0
90						2	3	5	5	6	6	6	6	7	7	7	7	7	7	7	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	6	5	1	0	0	0
100						1	2	5	6	6	7	7	7	8	8	8	9	9	9	9	9	9	9	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	10	8	3	1	0
115							1	3	6	7	8	8	9	9	10	10	11	11	11	11	12	12	12	12	12	12	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	13	11	4	2
130								2	4	7	8	9	10	11	11	12	13	13	13	14	14	14	15	15	15	15	16	16	16	16	16	16	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	17	14	11
145									2	4	8	10	11	12	13	14	14	15	16	16	17	17	17	18	18	18	19	19	19	19	20	20	20	20	20	20	21	21	21	21	21	21	21	21	21	21	21	21	21	21	20	20	20	17
160										2	5	10	11	13	14	15	16	17	18	18	19	20	20	21	21	21	22	22	22	23	23	23	23	23	23	23	23	23	23	23	23	23	23	23	23	23	23	23	22	22	22	21	21
175											3	5	11	13	14	16	17	18	19	20	21	22	23	23	24	24	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	25	24	24	23	23	22
190												3	6	12	14	16	18	19	21	22	23	24	25	26	27	27	28	27	27	27	27	27	27	27	27	27	27	27	27	27	27	27	27	27	27	27	26	26	25	25	25	24	24
205													3	7	13	16	18	20	21	23	24	26	27	28	29	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	30	29	29	28	28	27	27	26	26	25	25
220														4	7	14	17	20	22	24	25	27	29	30	31	32	32	32	32	32	32	32	32	32	32	32	32	32	32	32	32	31	30	30	29	28	28	27	27	26	26	25	25
235															4	8	16	19	21	24	26	28	30	31	33	34	34	34	34	34	34	34	34	34	34	34	34	34	34	33	32	31	31	30	29	29	28	28	27	27	26	26
250																4	8	17	20	23	26	28	30	33	34	36	37	37	36	36	36	36	36	36	36	36	36	36	35	34	34	33	32	31	30	30	29	29	28	27	27	27
265																	5	9	18	22	25	28	31	33	35	37	39	39	39	39	39	39	39	39	39	39	39	39	39	38	37	36	35	34	33	32	31	31	30	29	28	28	27
280																		5	10	19	23	27	30	33	36	38	40	41	41	41	41	41	41	41	41	41	41	40	39	37	36	35	34	33	33	32	31	30	30	29	28	28
295																			5	10	21	25	29	32	35	38	41	43	43	43	43	43	43	43	43	43	43	42	41	39	38	37	36	35	34	33	32	31	31	30	29	29
310																				6	11	22	26	30	34	38	41	44	45	45	45	45	45	45	45	45	45	44	43	41	40	38	37	36	35	34	33	32	31	30	30
325																					6	11	23	28	32	36	40	43	47	48	48	48	48	48	48	48	48	47	45	43	42	40	39	38	37	35	34	34	33	32	31	31
340																						6	12	25	29	34	38	42	46	49	50	50	50	50	50	50	49	47	45	44	42	41	39	38	37	36	35	34	33	32	32
355																							7	13	26	31	36	41	45	49	50	52	52	52	52	52	52	50	48	46	44	43	41	40	38	37	36	35	34	33	33
370																								7	13	27	33	38	43	47	50	52	53	54	54	54	54	53	51	49	47	45	43	42	40	39	38	37	35	35	34
385																									7	14	28	34	40	45	50	52	53	55	56	57	57	57	54	51	49	47	45	44	42	41	39	38	37	36	35
400																										8	15	30	36	42	47	52	53	55	56	58	59	59	58	55	52	50	48	46	44	42	41	40	38	37	36
415																											8	15	31	37	43	49	53	55	56	58	59	61	61	58	55	53	50	48	46	44	43	41	40	39	38
430																												8	16	32	39	45	51	55	56	58	59	61	62	63	59	56	53	51	49	47	45	43	42	40	39
445																													9	16	33	41	47	54	56	58	59	61	62	64	63	60	57	54	51	49	47	45	44	42	41
460																														9	17	35	42	49	56	58	59	61	62	64	65	64	61	57	55	52	50	48	46	44	43
475																															9	18	36	44	51	58	59	61	62	64	65	65	65	61	58	55	53	50	48	46	45
490																																10	18	37	45	53	59	61	62	64	65	65	65	65	62	59	56	53	51	49	47
505																																	10	19	39	47	55	61	62	64	65	65	65	65	65	63	59	56	54	51	50
520																																		10	20	40	49	57	62	64	65	65	65	65	65	65	63	60	57	54	52

CONVY-DCDC-800V-15-RA-00_PowerMap - Boost Mode (kW)

Buck mode (in kW)

Vlow \ Vhigh	40	50	60	70	80	90	100	115	130	145	160	175	190	205	220	235	250	265	280	295	310	325	340	355	370	385	400	415	430	445	460	475	490	505	520	535	550	565	580	595	610	625	640	655	670	685	700	715	730	745	760	775	790	800
35																																																							
40											1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	2	2	2	2	2	2	2	2	2	2	2	2	2	2	1	0	0	0	0	0	0	0
45					1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0
50				1	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	2	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	3	2	1	0	0	0	0	0	0
60				1	2	3	3	3	3	3	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	4	3	0	0	0	0	0	0	0
70					2	3	3	4	4	4	5	5	5	5	5	5	5	5	5	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	5	2	0	0	0	0	0	0
80					1	3	4	4	5	5	5	6	6	6	6	6	6	7	7	7	7	7	7	7	7	7	7	7	7	7	7	7	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	8	5	3	0	0	0	0
90						2	3	5	5	6	6	7	7	7	8	8	8	8	8	9	9	9	9	9	9	9	9	9	9	9	9	9	9	9	9	9	10	10	10	10	10	10	10	10	10	10	10	10	10	8	6	2	0	0
100						1	3	5	6	6	7	8	8	8	9	9	9	9	10	10	10	10	10	10	11	11	11	11	11	11	11	11	11	11	12	12	12	12	12	12	12	12	12	12	12	12	12	12	12	10	4	2	0
115							2	3	6	7	8	9	9	10	10	11	11	12	12	12	12	13	13	13	13	14	14	14	14	14	14	15	15	15	15	15	15	15	15	15	15	15	15	15	15	16	16	16	16	13	6	2
130								2	4	7	8	9	10	11	12	12	13	14	14	14	15	15	16	16	16	16	17	17	17	17	18	18	18	18	18	18	19	19	19	19	19	19	19	19	19	19	19	19	19	19	16	13
145									2	4	8	10	11	12	13	14	15	15	16	17	17	18	18	19	19	19	20	20	20	21	21	21	21	22	22	22	22	22	22	22	22	22	22	22	22	22	22	22	22	22	22	22	20
160										2	5	9	11	12	14	15	16	17	18	19	19	20	21	21	22	22	23	23	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	24	23
175											3	5	10	12	14	15	17	18	19	20	21	22	23	24	25	25	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	26	25	25	24	24	24
190												3	6	11	13	15	17	19	20	22	23	24	25	26	27	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	28	27	27	26	26	25	25	24	24
205													3	6	12	15	17	19	21	23	24	26	27	28	29	30	31	31	31	31	31	31	31	31	31	31	31	31	31	30	30	29	29	28	28	27	27	26	26	25	25
220														3	7	13	16	19	21	23	25	27	28	30	31	32	33	33	33	33	33	33	33	33	33	33	33	33	32	32	31	30	30	29	28	28	27	27	26	26	26
235															4	7	14	17	20	23	25	27	29	31	33	34	35	35	35	35	35	35	35	35	35	35	35	34	34	33	32	31	31	30	29	29	28	28	27	27	26
250																4	7	15	19	22	24	27	29	32	34	36	37	37	37	37	37	37	37	37	37	37	36	35	34	33	32	32	31	30	30	29	28	28	27	27
265																	4	8	16	20	23	26	29	32	34	36	39	40	40	40	40	40	40	40	40	39	37	36	35	34	34	33	32	31	31	30	29	29	28	28
280																		4	8	17	21	25	28	31	34	37	39	42	42	42	42	42	42	42	42	40	39	38	37	36	35	34	33	32	32	31	30	30	29	29
295																			4	9	18	22	26	30	33	36	39	42	44	44	44	44	44	44	44	42	41	40	38	37	36	35	34	33	33	32	31	30	30	29
310																				4	9	19	24	28	32	35	39	42	45	46	46	46	46	46	46	45	43	42	40	39	38	37	36	35	34	33	32	31	31	30
325																					5	10	20	25	29	34	37	41	44	48	49	49	49	49	49	47	45	44	42	41	39	38	37	36	35	34	33	32	32	31
340																						5	10	21	26	31	35	40	43	47	50	51	51	51	51	51	50	48	46	44	43	41	40	39	37	36	35	34	33	33	32
355																							5	11	22	28	33	37	42	46	50	51	53	53	53	53	53	51	48	46	45	43	42	40	39	38	37	36	35	34	33
370																								5	11	23	29	34	39	44	48	51	53	54	55	55	55	54	51	49	47	45	44	42	41	39	38	37	36	35	34
385																									5	11	24	30	36	41	46	51	53	54	56	57	58	57	54	52	50	48	46	44	42	41	40	38	37	36	36
400																										6	12	25	31	37	43	48	53	54	56	57	59	60	58	55	53	50	48	46	44	43	41	40	39	38	37
415																											6	12	26	32	39	44	50	54	56	57	59	60	62	59	56	53	51	49	47	45	43	42	40	39	38
430																												6	13	27	34	40	46	52	56	57	59	60	62	63	60	57	54	51	49	47	45	44	42	41	40
445																													6	13	28	35	42	48	54	57	59	60	62	63	64	60	57	54	52	50	48	46	44	43	42
460																														6	13	29	36	43	50	56	59	60	62	63	65	64	61	58	55	52	50	48	46	44	43
475																																6	14	29	37	45	51	58	60	62	63	65	65	65	62	58	56	53	51	49	47	45
490																																	6	14	30	38	46	53	60	62	63	65	65	65	65	62	59	56	53	51	49	48
505																																		7	14	31	39	47	55	62	63	65	65	65	65	65	63	60	57	54	52	50
520																																			7	15	32	41	49	57	63	65	65	65	65	65	65	64	60	57	55	53

CONVY-DCDC-800V-15-RA-00_PowerMap - Buck Mode (kW)

Each product reference has its own Power Map. For any detailed information please contact our sales team:
contact@tame-power.com

All the information contained in this document is the exclusive property of TAME-POWER and cannot be reproduced or communicated with a third party without the express written authorization of TAME-POWER. TAME-POWER reserves the right to make any changes without prior notice. Tame-Power is a registered trademark of TRONICO.
STRICTLY CONFIDENTIAL TAME-POWER